

# Flashing Siren

## Dual Way Communication

### MD-334R



- Double flashing light.
- Built-in tweeter.
- 2-way communication with alarm control panel.
- Can arm/disarm by remote controller.
- with tamper alarm.
- Can enroll 16 wireless devices.

MD-334R is a kind of alarm device with strong popularity. Its power from the adapter or external lithium batteries via wireless signal. Its communicate with alarm panel, detector, remote etc. Which work with the same frequency as the siren and achieve flash light and alarm sound when alarm occurs. And it also give prompt sound when the remote which have code with the siren to arm or disarm. This siren has anti-tamper function to avoid intentional damage or dismantle. When alarm happens it make high alarm sound. Commonly used in the outdoor of the house, office, factory, shops etc.

## Specification

### Overview

Wireless communication distance	100m (In the open area)	Alarm loudness	about 100dB
Working voltage	DC12~15V	Sirens ringing time	150 seconds
backup power	7.4V/1000mAh(Rechargeable lithium battery)	Size	(L*W*H)230*165*55mm
Quiescent Current	<15mA	Trigger mode	When arm by remote, the detector and magnetic contact etc. which have coded with the siren will alarm when they are triggered.Or the panel send signal to the siren,and it makes alarm. It can code with Max 16 wireless Device.
Working current	<1.2A		
Debugging method	ASK		
Working frequency	433/868MHz(Optional)		