

# SMOKE & GAS

Detector Wired Series

## MD-2003



This product selects the most advanced small current imported gas sensor, can detect the leak gas in a timely manner, accurately reflect the alarm situation. Elegant streamlined design, convenient installation, can also be used as part of the home decoration.

## Specification

### Overview

Test gas natural gas

Power supply DC 9V-16V

Speaker volume  $\geq 70\text{dB/m}$ (1 meter ahead)

Alarm concentration 15% LEL

Recovery concentration 8% LEL

Working environment  $-10^{\circ}\text{C}\sim 40^{\circ}\text{C}$

Relative humidity  $\leq 90\% \text{RH}$

Stability long-term work alarm concentration is not greater than  $\pm 5\% \text{LEL}$

Repeatability Repeat test alarm concentration no more than  $\pm 5\% \text{LEL}$

Alarm concentration error no more than  $\pm 3\% \text{LEL}$

Alarm mode sound and light alarm, the output wireless signal

Power consumption no more than 5W